

TouchBoard G80-11900



Models may vary from the image shown

Compact keyboard with built-in touchpad

The multifunctional TouchBoard is the perfect solution for limited spaces in situations requiring the functions of a "mouse". Particularly in hard industrial applications, the Cherry keyboard shows what she is made of. The model combines outstanding quality with long service life and precise, easy-to-operate touchpad.

Key benefits

- Individual keys with Gold Crosspoint contacts (MX technology)
- Designed for continuous usage - over 50 mill. confirmations per key
- Robust and reliable
- Space-saving and ergonomic
- Ideal for limited space and 19" applications
- Can be used with the standard drivers of the operating system
- USB keyboard: the following keys can be programmed freely using KeyM@n software (software macros) in 3 levels (single confirmation in combination with "CTRL", in combination with "SHIFT"): function keys "F1"- "F12", "INSERT", "DELETE", "POSITION1", "END", "PAGE-UP", "PAGE-DOWN", "PRINT", "PAUSE", comma and zero in the numeric field.

Technical Data:

Layout (country or language):

Product dependant, see table "Models"

Housing colour:

Product dependant, see table "Models"

Key colour:

Product dependant, see table "Models"

Weight (product):

approx. 1000 g

Total weight (with packaging):

approx. 1200 g

Cable Length:

approx. 1.75 m

Storage Temperature:

-20°C to 60°C

Operating Temperature:

0°C to 50°C

Current Consumption:

Product dependant, see table "Models"

Interface:

Product dependant, see table "Models"

Product approvals:

Product dependant, see table "Models"

System requirements:

Product dependant, see table "Models"

Delivery Volume:

Product dependant, see table "Models"

Dimensions (product):

approx. 415 x 193 x 37 mm

Packaging dimensions:

approx. 447 x 250 x 45 mm

Reliability:

- MCBF > 10 bill. operations
- MTBF > 874,000 hours

Touchpad:

- Resolution: 1000 dpi
- Number of Keys: 2

Keyboard:

- Key technology: MX
- Service life, standard key: > 50 million key operations
- Operation characteristics: Linear
- Inscription technology: Laser
- Inscription layout: Normal
- Number of Keys: Product dependant, see table "Models"

Packaging Unit:

- Number of products in the master package: 66
- Number of master packages per pallet: 2

Warranty:

2 years

Errors, technical changes and delivery possibilities excepted. Technical information refers only to the specifications of the products. Features may differ from the information provided.

Models:

(possible country/layout versions, others available on request)

	Product name	Order number	Layout (country or language)	Housing colour	Key colour	Current Consumption	Interface	Product approvals	System requirements	Delivery Volume	Number of Keys
1	TouchBoard G80-11900	G80-11900LPMBE-0	Belgium	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
2	TouchBoard G80-11900	G80-11900LPMBE-2	Belgium	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
3	TouchBoard G80-11900	G80-11900LPMCH-0	Switzerland	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
4	TouchBoard G80-11900	G80-11900LPMCH-2	Switzerland	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
5	TouchBoard G80-11900	G80-11900LPMDE-0	Germany	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
6	TouchBoard G80-11900	G80-11900LPMDE-2	Germany	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
7	TouchBoard G80-11900	G80-11900LPMDK-0	Denmark	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
8	TouchBoard G80-11900	G80-11900LPMDK-2	Denmark	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
9	TouchBoard G80-11900	G80-11900LPMES-0	Spain	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
10	TouchBoard G80-11900	G80-11900LPMES-2	Spain	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
11	TouchBoard G80-11900	G80-11900LPMEU-0	US English with EURO symbol	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	104

	Product name	Order number	Layout (country or language)	Housing colour	Key colour	Current Consumption	Interface	Product approvals	System requirements	Delivery Volume	Number of Keys
12	TouchBoard G80-11900	G80-11900LPMEU-2	US English with EURO symbol	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	104
13	TouchBoard G80-11900	G80-11900LPMFR-0	France	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
14	TouchBoard G80-11900	G80-11900LPMFR-2	France	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
15	TouchBoard G80-11900	G80-11900LPMGB-0	UK	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
16	TouchBoard G80-11900	G80-11900LPMGB-2	UK	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
17	TouchBoard G80-11900	G80-11900LPMGR-0	Greece	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
18	TouchBoard G80-11900	G80-11900LPMGR-2	Greece	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
19	TouchBoard G80-11900	G80-11900LPMIT-0	Italy	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
20	TouchBoard G80-11900	G80-11900LPMIT-2	Italy	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
21	TouchBoard G80-11900	G80-11900LPMNO-0	Norway	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
22	TouchBoard G80-11900	G80-11900LPMNO-2	Norway	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
23	TouchBoard G80-11900	G80-11900LPMPO-0	Portugal	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105

	Product name	Order number	Layout (country or language)	Housing colour	Key colour	Current Consumption	Interface	Product approvals	System requirements	Delivery Volume	Number of Keys
24	TouchBoard G80-11900	G80-11900LPMPO-2	Portugal	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
25	TouchBoard G80-11900	G80-11900LPMRB-0	English (US) / Cyrillic	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	104
26	TouchBoard G80-11900	G80-11900LPMRB-2	English (US) / Cyrillic	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	104
27	TouchBoard G80-11900	G80-11900LPMSF-0	Sweden / Finland	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
28	TouchBoard G80-11900	G80-11900LPMSF-2	Sweden / Finland	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
29	TouchBoard G80-11900	G80-11900LPMTS-0	Czech Republic	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
30	TouchBoard G80-11900	G80-11900LPMTS-2	Czech Republic	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy	105
31	TouchBoard G80-11900	G80-11900LTMBE-0	Belgium	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
32	TouchBoard G80-11900	G80-11900LTMBE-2	Belgium	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
33	TouchBoard G80-11900	G80-11900LTMCH-0	Switzerland	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
34	TouchBoard G80-11900	G80-11900LTMCH-2	Switzerland	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105

	Product name	Order number	Layout (country or language)	Housing colour	Key colour	Current Consumption	Interface	Product approvals	System requirements	Delivery Volume	Number of Keys
35	TouchBoard G80-11900	G80-11900LTMDE-0	Germany	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
36	TouchBoard G80-11900	G80-11900LTMDE-2	Germany	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
37	TouchBoard G80-11900	G80-11900LTMDK-0	Denmark	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
38	TouchBoard G80-11900	G80-11900LTMDK-2	Denmark	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
39	TouchBoard G80-11900	G80-11900LTMES-0	Spain	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
40	TouchBoard G80-11900	G80-11900LTMES-2	Spain	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
41	TouchBoard G80-11900	G80-11900LTMEU-0	US English with EURO symbol	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	104
42	TouchBoard G80-11900	G80-11900LTMEU-2	US English with EURO symbol	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	104
43	TouchBoard G80-11900	G80-11900LTMFR-0	France	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105

	Product name	Order number	Layout (country or language)	Housing colour	Key colour	Current Consumption	Interface	Product approvals	System requirements	Delivery Volume	Number of Keys
44	TouchBoard G80-11900	G80-11900LTMFR-2	France	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
45	TouchBoard G80-11900	G80-11900LTMGB-0	UK	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
46	TouchBoard G80-11900	G80-11900LTMGB-2	UK	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
47	TouchBoard G80-11900	G80-11900LTMGR-0	Greece	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
48	TouchBoard G80-11900	G80-11900LTMGR-2	Greece	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
49	TouchBoard G80-11900	G80-11900LTMIT-0	Italy	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
50	TouchBoard G80-11900	G80-11900LTMIT-2	Italy	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
51	TouchBoard G80-11900	G80-11900LTMNO-0	Norway	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
52	TouchBoard G80-11900	G80-11900LTMNO-2	Norway	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105

	Product name	Order number	Layout (country or language)	Housing colour	Key colour	Current Consumption	Interface	Product approvals	System requirements	Delivery Volume	Number of Keys
53	TouchBoard G80-11900	G80-11900LTMPO-0	Portugal	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
54	TouchBoard G80-11900	G80-11900LTMPO-2	Portugal	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
55	TouchBoard G80-11900	G80-11900LTMRB-0	English (US) / Cyrillic	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	104
56	TouchBoard G80-11900	G80-11900LTMRB-2	English (US) / Cyrillic	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	104
57	TouchBoard G80-11900	G80-11900LTMSF-0	Sweden / Finland	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
58	TouchBoard G80-11900	G80-11900LTMSF-2	Sweden / Finland	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
59	TouchBoard G80-11900	G80-11900LTMTS-0	Czech Republic	light gray	light gray	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
60	TouchBoard G80-11900	G80-11900LTMTS-2	Czech Republic	black	black	typ. 35 mA (keyboard), typ. 3 mA (touchpad)	PS/2 (keyboard), PS/2 (mouse, trackball, touchpad)	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE, BSMI	PS/2 connections for keyboard and mouse	Operating instructions in hard copy, Adapter PS/2 to DIN(AT), Adapter PS/2 to RS 232	105
61	TouchBoard G80-11900	G80-11900LUMBE-0	Belgium	light gray	light gray	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
62	TouchBoard G80-11900	G80-11900LUMBE-2	Belgium	black	black	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
63	TouchBoard G80-11900	G80-11900LUMCH-0	Switzerland	light gray	light gray	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105

	Product name	Order number	Layout (country or language)	Housing colour	Key colour	Current Consumption	Interface	Product approvals	System requirements	Delivery Volume	Number of Keys
64	TouchBoard G80-11900	G80-11900LUMCH-2	Switzerland	black	black	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
65	TouchBoard G80-11900	G80-11900LUMDE-0	Germany	light gray	light gray	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
66	TouchBoard G80-11900	G80-11900LUMDE-2	Germany	black	black	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
67	TouchBoard G80-11900	G80-11900LUMDK-0	Denmark	light gray	light gray	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
68	TouchBoard G80-11900	G80-11900LUMDK-2	Denmark	black	black	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
69	TouchBoard G80-11900	G80-11900LUMES-0	Spain	light gray	light gray	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
70	TouchBoard G80-11900	G80-11900LUMES-2	Spain	black	black	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
71	TouchBoard G80-11900	G80-11900LUMEU-0	US English with EURO symbol	light gray	light gray	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	104
72	TouchBoard G80-11900	G80-11900LUMEU-2	US English with EURO symbol	black	black	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	104
73	TouchBoard G80-11900	G80-11900LUMFR-0	France	light gray	light gray	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
74	TouchBoard G80-11900	G80-11900LUMFR-2	France	black	black	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
75	TouchBoard G80-11900	G80-11900LUMGB-0	UK	light gray	light gray	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
76	TouchBoard G80-11900	G80-11900LUMGB-2	UK	black	black	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
77	TouchBoard G80-11900	G80-11900LUMGR-0	Greece	light gray	light gray	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
78	TouchBoard G80-11900	G80-11900LUMGR-2	Greece	black	black	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
79	TouchBoard G80-11900	G80-11900LUMIT-0	Italy	light gray	light gray	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105

	Product name	Order number	Layout (country or language)	Housing colour	Key colour	Current Consumption	Interface	Product approvals	System requirements	Delivery Volume	Number of Keys
80	TouchBoard G80-11900	G80-11900LUMIT-2	Italy	black	black	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
81	TouchBoard G80-11900	G80-11900LUMNO-0	Norway	light gray	light gray	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
82	TouchBoard G80-11900	G80-11900LUMNO-2	Norway	black	black	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
83	TouchBoard G80-11900	G80-11900LUMPO-0	Portugal	light gray	light gray	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
84	TouchBoard G80-11900	G80-11900LUMPO-2	Portugal	black	black	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
85	TouchBoard G80-11900	G80-11900LUMRB-0	English (US) / Cyrillic	light gray	light gray	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	104
86	TouchBoard G80-11900	G80-11900LUMRB-2	English (US) / Cyrillic	black	black	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	104
87	TouchBoard G80-11900	G80-11900LUMSF-0	Sweden / Finland	light gray	light gray	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
88	TouchBoard G80-11900	G80-11900LUMSF-2	Sweden / Finland	black	black	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
89	TouchBoard G80-11900	G80-11900LUMTS-0	Czech Republic	light gray	light gray	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105
90	TouchBoard G80-11900	G80-11900LUMTS-2	Czech Republic	black	black	max. 100 mA	USB	cURus, c-tick, VCCI, CE, FCC, ÜG-VDE	USB connection	Operating instructions in hard copy	105